

Digital Signage SignShow D5000

D5000 Advantages

- SVGA to Digital 1080p
- Flexible Scheduling Capability
- Multi-cast video streaming
- Integrated multi-standard video decoder
- RSS and Weather ticker support
- Player Security/Content Upload Login
- Touch button Design Preview
- Wireless ready
- Multiple Video, Image and Audio Support
- Fanless Design (Low Power)
- Auto Content Update by FTP
- Player Control by Web Page
- Multi Language
- Drag and drop layout design
- On-Screen Layout Preview

Flexibility

The SignShow D5000 advanced digital signage player can display a combination of Video, Graphics, Tickers, Date/Time and Background simultaneously. Zone layouts can be user definable or from built-in templates or saved user templates.

Tickers can also be horizontal or vertical, left to right or right to left scrolling and even static. The player also has full network capability to allow remote management content update, scheduling and reporting.

Full player and software security login is provided both at player level and content upload so you have full control of your signage. The D5000 supports FTP upload for overnight uploads and also local LAN selectable load balance for larger content uploads.

With Wireless setup built into the firmware users just need a low cost USB Wireless or 3G Dongle to get full wireless upload and control plus live RSS and Weather feeds. This makes the D5000 far more flexible for kiosks and other digital signage installs that cannot get access to a wired LAN network or running cabling across a building.

Simplicity

InfoSAP Creator content creation software that's bundle with the D5000 enables users to easily design, preview, publish and manage the signage message. With touch button preview you see your design in an instant and layout preview helps you design the perfect message.

Advanced Digital Signage High Definition Media Player

Green

With low power fanless design and the compact size, the D5000 makes an immensely powerful solution that is easy to mount and place in most signage deployments. The D5000 is ideal for businesses looking for an alternative to PC based signage systems.

InfoSAP Highlights

- Windows XP, Vista 32/64bit and Windows 7
- Onscreen Preview Mode
- Drag and Drop Video, Graphics and Sound files
- Ticker (left to right, right to left, top to bottom and Static)
- RSS Support
- See before Commit Preview Mode

InfoSAP Program Creator

The InfoSAP Creator software application enables you to design, schedule, distribute and display a wide variety of content for your digital signage.

The user-friendly drag and drop interface in InfoSAP Creator, makes it easy to use multiple audio, video, graphics and tickers (text or RSS) and then combine them to run simultaneously. Design your signage content by simply selecting from either the many standard templates or design your own and save to use again.


With its instant touch button preview and an on screen layout preview you're always in control of your design. The "Preview before Commit" uploading option gives you total control. InfoSAP Creator also provides sophisticated content management capabilities which make broadcasting information or digital advertising extremely simple.



Optoma is a world leading designer and manufacturer o

D5000 SPECIFICATIONS

Model	D5000
DC Adapter	12V DC, 2.5A
Power Consumption	Power On: 15W - Stand By: 1W
OS	Linux
RTC	Schedule On/Off
RAM	256 MB
Flash	8 MB
Storage Interface	SD Card (SDHC, Max Capacity 16GB)
Resolution	Up to 1080P
Operation Temperature	$0 \sim 40$ degree C
Inputs & Outputs	
Video Input	S-Video (mini Dim, 7 Pin)
Video Output	DVI-I, No HDCP
Audio Input	Stereo Mini Jack
Audio Output	Stereo Mini Jack
Communication Interface with Display	RS232C 9 Pin, Tx and Rx only (Factory programmable)
Network (LAN)	RJ45, No wake on LAN function
USB	USB 2.0 Host, (Mass storage class only)
IR input for remote	Yes, alternative usage: Wired IR
Content Management	
Screen Layout	Videos, Graphics, Text Tickers, RSS, Date/Time, Background (* Outsource Landscape only)
Video	WMV3 (Windows Media [®] Video 9), WMVA (Advanced profile), MPEG-1, MPEG-2, MPEG-4 (H.264), MOV (H.264), Flash Video (.FLV)
Audio	MP3, WMA9, AAC
Graphic	BMP, PNG, JPEG
Text Ticker	Variable scrolling speed, direction and position, Single and/or Multiple lines
Playlist	Scheduling Playback, Endless Loop Playback, Auto Play after power on
Player Dimensions (mm)	248 (W) x 138.4 (D) x 34 (H)
Carton Dimensions (mm)	Inner box: 335 (W) x 252 (D) x 131 (H) Outer box: 550 (W) x 350 (D) x 278 (H)
Net Weight	0.9 kg
Gross Weight	2.3 kg





Publish over WAN or LAN




SignShow D5000 Inputs / Outputs

- 1 Power
- 2 SD Card Slot
- 3 S-Video
- 4 DVI-I
- 5 USB
- 6 LAN
- 7 Power LED
- 9 Wired IR (Optional)10 RS232

8 Power LED

- 11 Reset
- 12 Audio-In
- 13 Audio-Out



Optoma Europe Ltd.

42 Caxton Way, Watford Business Park, Watford, Hertfordshire, UK. WD18 8QZ, Tel: +44 (0) 1923 691800

www.optoma.co.uk

Copyright © 2011, Optoma Europe Ltd. All other product names and company names used herein are for identification purposes only and may be trademarks or registered trademarks of their respective owners. All specifications are subject to change without notice, errors and omissions excepted. Some images may be simulated.